

# MOUNTED BALL BEARING APPLICATION GUIDE

## MOUNTING INSTRUCTIONS

Proper mounting of ball bearing units is critical to unit performance. Failure to follow accepted mounting practice may result in poor performance and short bearing life.

Good engineering and design practice does not recommend the application of more than two bearings to support any shaft. Where more than two bearings are used to support the same shaft, it is possible to induce heavy bearing overloads. In these cases, extreme care must be taken to line up bearings in both the vertical and horizontal planes. When the recommended two bearings are used, alignment is not as critical. Moline Bearing self-aligning mounted bearing units will compensate for minor differences in mounting structure.

For best results, use turned and ground shafts that are free of rough spots and burrs. If an old shaft is used, mount bearing units on a relatively smooth and unworn section.

Prior to mounting, clean both the shaft and the bearing bore. Coat the shaft with a small amount of oil. Slide the bearing unit on the shaft. Do not hammer the ends of the inner race. If necessary to apply some force in mounting, use a soft metal bar or pipe against the inner race only. Tap the bearing unit into place.

Tighten the two set screws securely to lock the bearing to the shaft. In applications where the bearing is subjected to heavy vibration, shock loads, or heavy thrust loads, then it may be desirable to file the shaft flat or drill the shaft slightly in the area where the set screws will contact.

## MAXIMUM SPEED

The maximum speed limits listed for the ball bearings can be found in the load rating table. These numbers should be used as a guide and considered along with other factors affecting bearing operation. Load characteristics, bearing lubrication, and temperature factors all influence bearing operation. It is possible that cataloged speed limits may be exceeded after factory engineers complete a complete application analysis.

## LUBRICATION

The proper lubrication of ball bearing units is critical in order to attain maximum bearing life expectancy. Moline ball bearing units need to be lubricated prior to use. They should be re-lubricated periodically, depending on the environment the bearing is exposed to. The following table can be used as a general guide. Experience will determine the best interval for each specific application.

### Lubrication Guide

OPERATING CONDITIONS	BEARING TEMPERATURES	GREASE INTERVAL
Clean	32°F to 120°F	6–12 Months
	120°F to 150°F	1–3 Months
	150°F to 200°F	1–4 Weeks
Dirty	32°F to 150°F	1–4 Weeks
	150°F to 200°F	Daily–1 Week
Moisture	32°F to 200°F	Daily–1 Week

The amount and type of lubricant used will affect bearing life. Lack of lubricant can lead to premature surface fatigue failures of balls and races. Over lubrication can damage seals and result in premature failure from contamination due to the inability of damaged seals to keep foreign material out of the bearing.

When lubricating bearings add grease slowly while the shaft is rotating. When the first sign of grease appears at the seals, the bearing will contain the correct amount of lubricant.

Bearings should not run in steady operation over 200°F and should not exceed 225°F for intermittent operation.

For unusual lubrication requirements or severe duty applications, contact Moline Bearing engineering for recommendations.



## MOUNTED BALL BEARING APPLICATION GUIDE

### BEARING SELECTION

Selection of the proper Moline bearing unit for a determined speed and load can be made by referring to the load rating tables. Proper selection is made by finding a bearing having the desired bore size which has a load rating equal to or greater than the radial or equivalent radial load required for the application.

The ratings shown in the rating tables are based on an average bearing life of 2500 hours. Average bearing life is approximately 5 times L10 life and is the life which may be expected from 50% or more of a given group of bearings operating under identical load conditions. Life expectancies for other than 2,500 hours average life may be determined by using the rating modification factors listed.

### BEARING LOADS

Radial loads and thrust force in combination are the principal load components of bearing applied loads. Moline ball bearing unit ratings are based upon the radial load capacity of the bearing. For applications where bearings are required to absorb thrust loads in addition to normal radial loads, the following considerations must be made concerning the magnitude of the thrust force.

When thrust loads are less than half the radial load, the equivalent load should be considered to be the same as the radial load. If the thrust load is equal to or greater than  $\frac{1}{2}$  the radial load, the equivalent load is determined by adding the two loads together. For thrust loads equal to or greater than the radial load, consult the factory.

#### EXAMPLE 1: RADIAL LOAD SERVICE LIFE

Select a mounted bearing flange block to meet the following application requirements.

- Shaft diameter of 1 inch
- Shaft speed is 1500 RPM
- Radial load requirement is 300 lbs.
- Average life requirement is 5000 hours

From the rating table located on the previous page, locate the series bearing corresponding to a one-inch shaft diameter and follow that line to the 1500 RPM column. The load capacity in this case is 860 lbs. These published radial load capacities are based on an average life of 2,500 hours

and must be modified to suit the application requirement 5,000 hours average life by using the proper multiplier from the chart below. Calculate the equivalent radial load capacity for 5,000 hours average life expectancy as follows:

$$\begin{array}{r} 860 \text{ lbs. radial capacity} \\ \times .794 \text{ 5,000 hours avg. life factor} \\ \hline 683 \text{ lbs. radial capacity} \\ \text{for 5,000 hours avg. life} \end{array}$$

#### EXAMPLE 2: COMBINATION RADIAL AND THRUST LOAD REQUIREMENT

Select a mounted pillow block to meet the following specifications.

- Shaft diameter of  $1\frac{3}{16}$
- A Combination load is applied consisting of
  - Radial Load of 400 lbs.
  - Thrust Load is 250 lbs.
- Shaft speed is 1000 RPM
- The average life requirement is 2,500 hours

From the load rating table on the previous page, locate the line with the series bearing corresponding to  $1\frac{3}{16}$  inch shaft size and follow this line to the right to the 1000 RPM column. The radial load capacity for the bearing is 1389 lbs.

Since the application average life is what the catalog rating charts are based on there's no need to apply further modification factors.

Because the applied thrust load of 250 lbs. is more than half of the applied radial load of 400 lbs., these loads must be added together to obtain the equivalent load requirement.

Equivalent load:  
400 lbs. + 250 lbs. = 650 lbs.

The equivalent radial requirement of 650 lbs. is less than the rated capacity, so the bearing size desired can be used.



**MOLINE BEARING CO.**

Post Office Box 99, Batavia, Illinois 60510, USA  
630.584.4600, 800.242.4633, 630.584.1999 fax  
www.molinebearing.com, sales@molinebearing.com

TEL # **800.242.4633**

127

# MOUNTED BALL BEARING RADIAL LOAD RATINGS

## Radial Load Ratings In Pounds

Information in this table shows load ratings at various RPM based on 500 hours minimum life to 2500 hours average life.

BEARING #	RADIAL LOAD RATING AT VARIOUS RPM											
	50	100	250	500	750	1000	1200	1500	2000	2400	3800	5000
201-204	2469	1962	1433	1146	992	904	860	794	727	683	595	529
205	2690	2138	1587	1257	1102	1014	926	860	794	749	639	551
206	3747	2976	2204	1741	1521	1389	1301	1212	1102	1036	904	816
207	4960	3924	2888	2293	2006	1830	1675	1587	1455	1367	1190	-----
208	5600	4453	3285	2601	2271	2072	1940	1808	1631	1543	1345	-----
209	6173	4894	3593	2866	2491	2271	2138	1984	1808	1697	-----	-----
210	6768	5357	3946	3130	2734	2491	2315	2182	1984	1852	-----	-----
211	8333	6614	4872	3924	3593	3064	2888	2690	2447	2293	-----	-----
212	10097	8002	5908	4674	4100	3726	3505	3241	2954	2778	-----	-----
213	11023	8752	6437	5115	4475	4056	3814	3549	3219	-----	-----	-----
214	11971	9502	7010	5555	4850	4409	4144	3858	3505	-----	-----	-----
215	12985	10295	7583	6019	5247	4784	4497	4167	3792	-----	-----	-----
218	18721	14859	10949	8690	7592	6898	6491	6026	5475	-----	-----	-----

## Modification Factors For Average Service Life And Load Conditions

LOAD CONDITIONS	AVERAGE LIFE (1,000 HOURS)													
	2.5	3	4	5	6	7	8	10	15	20	25	30	40	50
Steady Load	1.00	.941	.855	.794	.747	.709	.679	.630	.550	.500	.464	.437	.397	.368
Light Shock	.900	.847	.770	.715	.672	.639	.611	.567	.495	.450	.418	.393	.357	.331
Moderate Shock	.700	.659	.599	.556	.523	.500	.475	.441	.385	.350	.325	.306	.278	.258

Factors are used to modify for loads that are not steady or for average life requirements beyond the standard 2500 hours shown in the Radial Load Rating table.

